# Eaton 63NZ02

Eaton Bussmann series low voltage D0 fuse, Time-delay, 400V, 63A, 100 kAIC, Non Indicating, fuse, Class C gL/gG, Holder, Copper, Ceramic body

| | |
|---|---|
| **PRODUCT NAME** | Eaton Bussmann series low voltage D0 fuse |
| **CATALOG NUMBER** | 63NZ02 |
| **UPC** | 051712836562 |
| **PRODUCT LENGTH/DEPTH** | 36 mm |
| **PRODUCT HEIGHT** | 15 mm |
| **PRODUCT WIDTH** | 15 mm |
| **PRODUCT WEIGHT** | 14.8 g |
| **COMPLIANCES** | GoST-R<br>CE Marked<br>RoHS Compliant |
| **CERTIFICATIONS** | IEC 60269<br>VDE<br>DIN EN 60269-3 (VDE 0636 Part 30)<br>DIN EN 60269-1 (VDE 0636 Part 10)<br>DIN VDE 0636-301 |

Powering Business Worldwide

| □□□□ | |
|---|---|
| **AMPERAGE RATING** | 63 A |
| **FUSE SIZE** | D02 |
| **BREAKING CAPACITY** | 50 kA |
| **RATED VOLTAGE AC** | 400 V |
| **CLASS** | Class C gL/gG |
| **FUSE TYPE** | NZ02 - Time delay |
| **UTILIZATION CATEGORY** | gL/gG (cable protection/equipment protection) |
| **ACCESSORY/SPARE PART TYPE** | 63GN02 Copper screw cap gauge piece |
| **COLOR** | Copper |
| **INTERRUPT RATING** | 50 kAIC |
| **FUSE INDICATOR** | Non-indicating |
| **CONNECTION** | Other |
| **CONSTRUCTION** | D02 |
| **CONSTRUCTION SIZE** | D02 |
| **FUSE SHAPE** | Bottle |
| **RESPONSE TIME** | Time-delay |
| **SUITABLE FOR** | E18 (D02) Fuse base<br>FRN02C Single-pole fuse base<br>FN02C Single-pole fuse base<br>FRN02-D Single-pole fuse base<br>FRN02-SD Single-pole fuse base<br>TFRN02C Three-pole fuse base<br>TFN02C Three-pole fuse base<br>TFRN02-D Three-pole fuse base<br>TFRN02-SD Three-pole fuse base |
| **MATERIAL** | White ceramic body |
| **MOUNTING METHOD** | Holder |
| **QUANTITY** | 10 |
| **VOLTAGE RATING** | 400 V |
| **TYPE** | fuse |
| **SPECIAL FEATURES** | Time-delay |
| **APPLICATION** | For domestic and general industrial applications |

| □□ | |
|---|---|
| DECLARATIONS OF CONFORMITY | eaton-low-voltage-d-fuse-declaration-of-conformity-uk251016en.pdf |

| | |
|---|---|
| □□□□: | |
| □□□□: | |
| □□□: | |
| □□: | |

□□□□ Eaton House
30 Pembroke Road
Dublin 4, □□□
Eaton.com

© 2026 □□ □□□□□□□□

□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□